Cordless Eartag Applicator Tag-Rex1.0





FEATURES AND HIGHLIGHS



Safety Button. Tag-Rex 1.0 will not function without pressing the safety button to operate the jaws for every ear tag placement, ensuring less chance of injuries.

Battery Life Indicator.



SPECIFICATIONS

Weight......0.76kg [1.68 lbs.] No Battery 1.10kg [2.44 lbs.] with Battery Tagging Speed.....Less then 1 second Tags/Charge......Approx: 2000 Motor RPM......25,000 Working Temperature.....-10°C to +60°C Battery......X21 21V 2.0 Ah Dimensions: Height:.....310mm[12.2"] Length:.....110mm[4.3"]

BENEFITS

- Avoids carpel tunnel syndrome
- Easy and quick maneuverability
- Precise ear-tagging each time
- Prevents unwanted tagging tears vs manual tagging

The Tag-Rex 1.0 is an electric ear-tagger for the implantation of ear tags. Placing ear tags with the Tag-Rex 1.0 avoids continuous strain and tired hands, reducing injuries to the operator. Placing ear tags precisely into the ear improves the result on the animal's ear, preventing unwanted tears. This cordless tool gives you exceptional maneuverability, which makes the tagging process for each operator much easier.

The Tool For Effortless Tagging

RELATED ACCESSORIES



ID# 66-1001-005.....Charger



ID# 66-1001-006.....Battery

Second Per Tag Implantation 2,000 Tags Per Charge

All specifications subject to change without prior notice All models and accessories are subject to stock on hand. Please check our Website, Call or Email for inquiries and/ or guestions.